



agile remotec

Features

1. Preprogram for 9 devices (TV/VCR/SAT&DSS/CD/LD/DVD/AV1/AV2/AV3).
2. Learn up to 240 commands.
3. 5 hard keys and 3 touch screen shortcuts.
4. EL backlight on LCD display and hard keys.
5. Light sensor to backlight for power conservation.
6. Beep sound feedback for key press.
7. Maximum 5 pages per device, maximum 16 keys per page, total max .70 commands for each device.
8. Editable key shape and location through PC software.
9. Smart function, Max 10 Smart, 30 commands per each Smart (including time delay).
10. Delay time for Smart function.
11. Real time clock.
12. Low battery indication.
13. Auto powered off.
14. Visible LED indicator for IR code transmission.
15. Password for security lock.
16. Rename/delete/move function of key label and device name.
17. TV volume control punch through function.
18. Custom page – user set most frequently used commands to form a customized page.
19. Clone function – remote-to-remote copy function.
20. PC Link function – PC-to-remote data upload/download function through external docking unit (Optional).
21. Nonvolatile memory for memory retention.
22. Interactive help screen.
23. Battery standard charging function through external adaptor.
24. Quick charge available through external docking unit only (Optional).

Technical Specification

1. Dimension : 50.5mm(W) x 220mm(H) x 23mm(D).
2. Touch panel area : 135mm x 36mm.
3. Touch Panel type : Analog resistive.
4. LCD resolution : 320 x 80, monochrome.
5. LCD viewing area : 129mm x 35mm.
6. LCD dot size : 0.31mm x 0.31mm.
7. EL backlight : Blue-green.
8. Memory : 4Mbit flash; 2Mbit SRAM.
9. Available memory for learning : 240 commands.
10. Available memory for Smart : 10 x 30 commands
11. Batteries : NiMH Rechargeable 1.2V, AAA x 4.
12. Battery Life: Approximately 1~3months (depends operating mode).
13. Battery charging time : 14 hours (standard charge); 4 hours (quick charge).